

松下MINAS A4交流伺服驱动器外配再生放电电阻规格表

驱动器型号	适配电机	电阻值	额定功率	内藏电阻值	
MADDT1205	MSMD5AZ***	100Ω	45W		
	MSMD012***	100Ω	45W		
	MQMA012***	50Ω	75W		
MADDT1207	MAMA012***	50Ω	75W		
	MSMD022***	50Ω	75W		
	MQMA022***	50Ω	75W		
	MHMD022***	50Ω	75W		
MBDDT2210	MAMA022***	50Ω	75W		
	MSMD042***	50Ω	75W		
	MQMA042***	50Ω	75W		
	MHMD042***	50Ω	75W		
MCDDT3520	MAMA042***	50Ω	75W	100Ω*	
	MSMD082***	50Ω	75W		
	MFMA042***	50Ω	75W		
	MHMA052***	50Ω	75W		
	MHMD082***	50Ω	75W		
MDDDT3530	MDMA082***	30Ω	150W	30Ω	
	MDMA102***	30Ω	150W		
	MHMA102***	30Ω	150W		
MDDDT5540	MAMA082***	30Ω	150W	30Ω	
	MSMA102***	30Ω	150W		
	MSMA152***	30Ω	150W		
	MDMA152***	30Ω	150W		
	MGMA092***	30Ω	150W		
	MFMA152***	30Ω	150W		
	MHMA152***	30Ω	150W		
MEDDT7364	MSMA202***	15Ω	400W	15Ω	
	MDMA202***	15Ω	400W		
	MFMA252***	15Ω	400W		
	MHMA202***	15Ω	400W		
MFDDTA390	MSMA302***	10Ω	400W	10Ω	
	MDMA252***	10Ω	400W		
	MDMA302***	10Ω	400W		
	MDMA352***	10Ω	400W		
	MGMA202***	10Ω	400W		
	MHMA302***	10Ω	400W		
MFDDTB3A2	MSMA402***	10Ω	400W	10Ω	
	MSMA502***	10Ω	400W		
	MDMA402***	10Ω	400W		
	MDMA452***	10Ω	400W		
	MDMA502***	10Ω	400W		
	MGMA302***	10Ω	400W		
	MGMA452***	10Ω	400W		
	MFMA452***	10Ω	400W		
	MHMA402***	10Ω	400W		
	MHMA502***	10Ω	400W		

- 建议：
- 1, 选配外部制动电阻时，尽量选与内部电阻值相同的，功率尽量选得大一些
  - 2, 应选配无感电阻
  - 3, 断开连接内部电阻的短接线，同时将Pr6C号参数改为1或2