

常见液晶屏 LVDS 接口定义

技术咨询: 0833-5552207

QQ: 286824456 350804300 458399680

讨论群: 40068583

客服群: 34730182

<http://www.wjel.net>

线序	类型	20P					30P							14P			
		SIN6		SIN8	DO6	DO8	SIN6	SIN8	DO6	DO8			SIN6				
1		VCC	VCC	VCC	VCC	VCC		NC	NC	VCC	VCC		VCC	VCC	RXO0-	VCC	1
2		VCC	VCC	VCC	VCC	VCC		VCC	VCC	VCC	VCC		VCC	VCC	RXO0+	VCC	2
3		GND	VCC	GND	GND	GND		VCC	VCC	GND	VCC		VCC	VCC	RXO1-	GND	3
4		GND	GND	GND	GND	GND		NC	NC	GND	NC		GND	NC	RXO1+	GND	4
5		R0-	GND	R0-	R0-	R0-		NC	NC	R0-	NC		GND	NC	RXO2-	R0-	5
6		R0+	R0-	R0+	R0+	R0+		NC	NC	R0+	NC		GND	NC	RXO2+	R0+	6
7		GND	R0+	GND	GND	R1-		NC	NC	GND	GND		NC	GND	GND	R1-	7
8		R1-	GND	GND	R1-	R1+		R0-	R0-	R1-	R0-		NC	R0-	ROXCLK	R1+	8
9		R1+	R1-	R1-	R1+	R2-		R0+	R0+	R1+	R0+		GND	R0+	ROXCLK	R2-	9
10		GND	R1+	R1+	GND	R2+		GND	GND	GND	R1-		RXO3+		RXO3-	R2+	10
11		R2-	GND	GND	R2-	CLK-		R1-	R1-	R2-	R1+		RXO3-	R1-	RXO3+	CLK-	11
12		R2+	R2-	GND	R2+	CLK+		R1+	R1+	R2+	R2-		ROXCLK+	R1+	RXE0-	CLK+	12
13		GND	R2+	R2-	GND	R01-		GND	GND	GND	R2+		ROXCLK-		RXE0+	GND	13
14		CLK-	GND	R2+	CLK-	R01+		R2-	R2-	CLK-	GND		RXO2+	R2-	GND	GND	14
15		CLK+	CLK-	GND	CLK+	R02-		R2+	R2+	CLK+	CLK-		RXO2-	R2+	RXE1-		15
16		NC	CLK+	GND	NC	R02+		GND	GND	GND	CLK+		RXO1+		RXE1+		16
17		NC	GND	CLK-	R03-	R03-		CLK-	CLK-	RS0-	GND		RXO1-	CLK-	GND		17
18		NC		CLK+	R03+	R03+		CLK+	CLK+	RS0+	R03-		RXO0+	CLK+	RXE2-		18
19		NC/G		GND	NC/G	CLK-		GND	GND	GND	R03+		RXO0-		RXE2+		19
20		NC/G		GND	NC/G	CLK+		NC	R03-	RS1-	RB0-		RXE3+	R03-	RXECLK-		20
21								NC	R03+	RS1+	RB0+		RXE3-	R03+	RXECLK+		21
22								NC	NC	GND	RB1-		RXECLK+		RXE3-		22
23								NC	NC	RS2-	RB1+		RXECK-	RB0-	RXE3-		23
24								NC	NC	RS2+	GND		RXE+	RB0+	GND		24
25								NC	NC	GND	RB2-		RXE2-		NC		25
26								NC	NC	CLK2-	RB2+		RXE1+	RB1-	NC		26
27								NC	NC	CLK2+	CLK2-		RXE1-	RB1+	NC		27
28								NC	NC		CLK2+		RXE0+		VCC		28
29								NC	NC		RB3-		RXE0-		VCC		29
30								NC	NC		RB3+		GND		VCC		30
例:																	例:

技术咨询: 0833-5552207

QQ: 286824456 350804300 458399680

讨论群: 40068583

客服群: 34730182

<http://www.wjel.net>